

# W-DMX™ Transmitter



W-DMX™ Transmitter works with W-DMX™ wireless wash lights, including WELL™ 2.0, to generate a wireless control signal. It features auto-ranging power from 100 to 240V, a locking IEC power connector and 3- and 5-pin DMX input-only connectors.

## FEATURES

- 3-pin and 5-pin DMX input/output connections
- 2.4 GHz frequency
- Wireless DMX transmission for up to one full 512-channel universe
- Omni-directional 2 dBi boost antenna

## SPECIFICATIONS

### Construction/Physical

- Dimensions: 6.2 x 3.5 x 2.3 in (158 x 89 x 59 mm)
- Exterior Color: Black
- Housing Material: Aluminum alloy

### Connections

- Power Connection: Edison (Local) plug to IEC
- Power Input: IEC
- Data Connectors: 3- and 5-pin XLR
- Cable Length (power): 5 ft (1.5 m)

### Control

- Control Protocol: DMX, W-DMX™
- DMX Channels: 1
- Frequency (operating): 2.4 GHz

### Electrical

- Input Voltage: 100 to 240 VAC, 50/60 Hz (auto-ranging)

### Certifications/Qualifications

- CE
- IP Rating: IP20, dry location

### What's Included

- W-DMX™ Transmitter
- IEC power cord